



SAĞLAMTEK
Aerospace & Defense Co.



BORAJ-MINI4 GNSS CRPA SYSTEM

**While others lose signal, our
partners stay on course**

Our solutions aren't just engineered — they're battle-hardened.





HIGHLIGHTS

- 4-array antenna system
- Improves the safety of satellite navigation in various platforms
- Prevents GNSS jamming caused by Jammers
- With anti-spoofing feature
- When used with SAJ, BORAJ provides up to 95 dB suppression of unwanted signals

Specifications

Parameter	Value
Effective Bands	L1, B1, E1 + L2 or L5
Suppression Rate 1-Source	75 dB
Suppression Rate 3-Source	70 dB
Effective Angles	Phi Angle from 0 ° to 360°, Theta Angle from -90° to +90°
Supply Voltage	12-15VDC
Power Consumption	14W

Operating Temperature	-40°C - +85°C
Storage Temperature	-45°C - +85°C
Humidity	95%
Waterproof	IP67
Dimensions	80 x 80 x 31 mm
Weight	230 gr
Interface	Micro-D (customizable)
Protocol	NMEA0183 Protocol
Interface	TTL

SAĞLAMTEK
AEROSPACE & DEFENCE CO.

Yasamkent Mahallesi 3053. Sokak No: 9
Çankaya / ANKARA

+90 505 237 33 81

info@saglamtek.com